

# How to implement **custom solar allocations**



## Pre-Sale

### At a site visit

Check and record for each tenancy and common area:

- ✓ Single or three-phase connection to the grid
- ✓ Phase (L1, L2, L3) of any single-phase connections

### With the body corporate

- ✓ Collect the % intended solar allocation for each tenancy and common area (e.g., lot entitlements)
- ✓ Discuss realistic expectations about achievable solar allocations

### Custom allocation tips (where practical)

- ✓ Assign different allocations per phase of any three-phase connections to SolShare to help balance allocations for other single-phase tenancies
- ✓ For common area, consider adding or removing its solar connection, or changing its solar allocation to better achieve tenancies' intended allocations
- ✓ Test connecting tenancies to different SolShares (multi-SolShare sites)
- ✓ Consider changing the phase of a single-phase tenancy's grid connection (aligning with any relevant regulations)

### System Design

- ✓ Design solar system to enable the intended allocations most effectively
- ✓ Use [Allume's custom allocation calculator](#) to find suitable allocation option/s
- ✓ Review the allocation option/s for improvement with the tips below

### Prior to contract sign-off

- ✓ Present the best solar allocation option/s to the body corporate for selection
- ✓ Obtain approval from the body corporate for the selected option (clearly defining the **agreed allocations** percentage for each tenancy and common area)

## Pre-Installation

### Installation Preparation

Provide all information in the [SolShare pre-installation checklist](#) to the installer, including:

#### On the SLD:

- ✓ Which SolShare to connect each tenancy and common area
- ✓ Which phases of each connection to connect to solar

#### For the [SolShare commissioning app](#):

- ✓ Select Custom Allocation as solar delivery method
- ✓ The **agreed allocations**

## Post-Installation

### Prior to System Handover

Using the [SolShare commissioning app](#):

- ✓ Check **agreed allocations** have been correctly set
  - Make any required adjustments to the allocation percentages